

# FIELD MAINTENANCE PRINT SET

"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1977, DIGITAL EQUIPMENT CORPORATION."

|                |                                     |
|----------------|-------------------------------------|
| B-TC-DLV11-F-J | ASYN. LINE INTERFACE (TC)           |
| A-PL-DLV11-F-Ø | ASYN. LINE INTERFACE (PL)           |
| D-UA-M8Ø28-Ø-Ø | DLV11-F ASYN. LINE INTERFACE, M8Ø28 |
| B-PL-M8Ø28-Ø-Ø | DLV11-F ASYN. LINE INTERFACE, M8Ø28 |
| Γ-CS-M8Ø28-Ø-1 | DLV11-F ASYN. LINE INTERFACE, M8Ø28 |
| A-PL-DLV11-F   | SHIPPING LIST, DLV11-F              |
| B-UA-BCØ5M-Ø-Ø | CABLE ASSEMBLY, BCØ5M               |
| D-UA-BCØ3L-Ø-Ø | CABLE ASSEMBLY, BCØ3L               |

[illegible]

DLVII-F  
Field Maintenance  
Print Set

## Digital Equipment Corporation

PRINT SET ORDER NO.  
MP00461

EN-01124-16 N675-1327

3 2 5 124

|           |          |      |                      |  |                         |                      |                                    |                           |  |  |  |  |  |  |  |  |           |            |                     |  |  |  |           |
|-----------|----------|------|----------------------|--|-------------------------|----------------------|------------------------------------|---------------------------|--|--|--|--|--|--|--|--|-----------|------------|---------------------|--|--|--|-----------|
| REVISIONS |          |      | USED ON OPTION/MODEL |  | DRN.<br>MIKE<br>MICHAUD | DATE<br>11 AUG<br>77 | TITLE:<br><br>ASYN. LINE INTERFACE |                           |  |  |  |  |  |  |  |  | SIZE<br>B | CODE<br>TC | NUMBER<br>DLV11-F-1 |  |  |  | REV.<br>A |
| DATE      | CHG. NO. | REV. |                      |  |                         |                      |                                    |                           |  |  |  |  |  |  |  |  |           |            |                     |  |  |  |           |
| 3-78      | DLV11F-1 | A    |                      |  | 11/03                   |                      | CHK'D<br>D. HEALY                  | DATE<br>11 AUG<br>77      |  |  |  |  |  |  |  |  |           |            |                     |  |  |  |           |
|           |          |      |                      |  |                         |                      |                                    |                           |  |  |  |  |  |  |  |  |           |            |                     |  |  |  |           |
|           |          |      |                      |  |                         |                      | PROJ. ENG.<br><i>M.D. Michaud</i>  | DATE<br><i>13 Aug. 77</i> |  |  |  |  |  |  |  |  |           |            |                     |  |  |  |           |
|           |          |      |                      |  |                         |                      | FIELD SERV.                        | DATE<br><i>22 Aug. 77</i> |  |  |  |  |  |  |  |  |           |            |                     |  |  |  |           |
|           |          |      |                      |  | SHEET 1 OF 1            |                      | <i>B Z</i>                         |                           |  |  |  |  |  |  |  |  |           |            |                     |  |  |  |           |

digital



# DIGITAL EQUIPMENT CORPORATION

## MAYNARD, MASSACHUSETTS

### PARTS LIST

|         |               |
|---------|---------------|
| MADE BY | M. MICHAUD    |
| DATE    | 11 AUG 77     |
| ENG     | M. A. Michaud |
| DATE    |               |

|         |                              |
|---------|------------------------------|
| CHECKED | D. HEATLY                    |
| DATE    | 11 AUG 77                    |
| PROD    |                              |
| DATE    | <del>11 AUG 77</del> 8-19-77 |

|              |   |
|--------------|---|
| SECTION      | 1 |
| ISSUED SECT. | 1 |

## QUANTITY VARIATION

[illegible][illegible]

|       |                               |
|-------|-------------------------------|
| TITLE | ASYN LINE INTERFACE (DLV11-F) |
|-------|-------------------------------|

|          |
|----------|
| ASSY NO. |
| NONE     |

|      |      |
|------|------|
| SIZE | CODE |
| A    | PL   |

NUMBER  
DLV11-F-Ø

|     |
|-----|
| REV |
| A   |

|         |          |
|---------|----------|
| ECO NO. | DLVII F- |
|         | 00001    |

SHEET 1 OF 1

DIST

# REWORK INSTRUCTIONS:

ECO #1

ETCH CUTS:

- 1-1 ES-5, SIDE 2
- 1-2 ES-6, SIDE 1 (UNDER ES)
- 1-3 ES-6, SIDE 2 (RIGHT SIDE OF PIN)
- 1-4 ES-8, SIDE 1 (UNDER ES)
- 1-5 ES-9, SIDE 2 (2 PLACES)
- 1-6 ES-1, SIDE 2
- 1-7 BOTTOM OF R21, SIDE 2 (LEFT SIDE)
- 1-8 E33-2, SIDE 2
- 1-9 WIRE ADDS (SIDE 1 UNLESS OTHERWISE NOTED)
- 1-9 FEED THRU AT RIGHT OF E17-B TO E6-15.
- 1-10 TOP OF C26 TO E5-8.
- 1-11 E5-8 TO FEED THROUGH BELOW E16-7.
- 1-12 E6-16 TO FEED THROUGH BELOW E11-7.
- 1-13 FEED THROUGH AT LEFT OF BOTTOM OF R21 TO FEED THROUGH BELOW C26.
- 1-14 FEED THROUGH AT RIGHT OF E5-9 TO E5-4.
- 1-15 FEED THROUGH AT RIGHT OF E5-9 TO E6-8.
- 1-16 E5-1 TO E6-6.
- 1-17 E5-2 TO E6-5.
- 1-18 E6-13 TO E6-12.
- 1-19 E6-9 TO E6-4.
- 1-20 E6-2 TO E11-10.
- 1-21 E6-14 TO E6-2.
- 1-22 TOP OF R21 TO TOP OF R22 (SEE NOTE 3)
- 1-23 BOTTOM OF R21 TO FEED THROUGH AT LEFT OF BOTTOM OF R21 (SEE NOTE 3).
- 1-24 FEED THROUGH BELOW E19-10 TO E24-B.
- 1-25 ("+" NEG. SIDE OF C2 TO "+" POS. OF C27.
- 1-26 E10-9 TO E14-7.
- 1-27 E33-2 TO E28-3.
- 1-28 E28-1 TO FEED THROUGH AT RIGHT OF E7-B.
- 1-29 E4-4 TO E11-11

ECO #2

COMPONENT DELETES SIDE 1:

- 2-1. DELETE R24 (PN 1303177)
- 2-2. DELETE I.C. E26 (PN 1911998-01)
- 2-3. DELETE I.C. E33 (PN 1911998-01)
- COMPONENT ADDS SIDE 1:
- 2-4. ADD R24 (PN 1300365)
- 2-5. ADD E26 (PN 1911998-02)
- 2-6. ADD E33 (PN 1911998-02)




## NOTES:

1. 8 HOLES .0145 (+.000-.005) HAYWARD ONLY
2. R41 NOT INSERTED
3. THIS CONNECTION IS MADE ON SIDE 2 BY BENDING THE RESISTER LEAD OVER TO THE ADJACENT FEED THROUGH.

| CHK | CHANGE NO | REV | DATE   | BY         | APP |
|-----|-----------|-----|--------|------------|-----|
| JA  | M8028-1   | B   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-2   | C   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-3   | D   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-4   | E   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-5   | F   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-6   | G   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-7   | H   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-8   | I   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-9   | J   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-10  | K   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-11  | L   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-12  | M   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-13  | N   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-14  | O   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-15  | P   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-16  | Q   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-17  | R   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-18  | S   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-19  | T   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-20  | U   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-21  | V   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-22  | W   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-23  | X   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-24  | Y   | 8-1-77 | N. MICHAUD |     |
| JA  | M8028-25  | Z   | 8-1-77 | N. MICHAUD |     |


## COMPONENT SIDE VIEW



| SIGNATURES                         | DATE   | digital |
|------------------------------------|--------|---------|
| DRN. Frank Smart                   | 8-1-77 |         |
| CHK'D. Frank Smart                 | 8-1-77 |         |
| ENG. M. J. J.                      | 8-1-77 |         |
| PROJ. ENG. J. J.                   | 8-1-77 |         |
| PROD. J. J.                        | 8-1-77 |         |
| SCALE 12-1                         |        |         |
| SHT. 1 OF 3                        |        |         |
| NEXT HIGHER ASSY. B-DD-145-128-0-0 |        |         |
| ETCH REV. B                        |        |         |
| P.C. DESIGN DATA BASE REV. B       |        |         |
| TITLE ASYNCHRONOUS LINE INTERFACE  |        |         |
| SIZE CODE D UA                     |        |         |
| NUMBER M8028-0-0                   |        |         |
| REV                                |        |         |



0 2832-11 40



|       |  |  |  |  |  |  |  |           |  |
|-------|--|--|--|--|--|--|--|-----------|--|
| TITLE |  |  |  |  |  |  |  | REV       |  |
| A L I |  |  |  |  |  |  |  | C         |  |
| DUA   |  |  |  |  |  |  |  | M8028-0-0 |  |
| 2-1   |  |  |  |  |  |  |  | 3         |  |
| 8     |  |  |  |  |  |  |  | 7         |  |
| 6     |  |  |  |  |  |  |  | 5         |  |
| 4     |  |  |  |  |  |  |  | 3         |  |
| 2     |  |  |  |  |  |  |  | 1         |  |

[illegible]

| LINE | ITEM | DOCUMENT NO.  | PART NO.   | DESCRIPTION                                 | QTY | REFERENCE DESIGNATORS  |
|------|------|---------------|------------|---------------------------------------------|-----|------------------------|
| 1    | 1    |               | 1912729-00 | DC   004   PROTOCOL,REG. SELECTOR           | 1   | E1                     |
| 2    | 2    |               | 1912730-00 | DC   003   INTERRUPT,2 CIRCUIT              | 1   | E10                    |
| 3    | 3    |               | 1913040-00 | DC   005   TRANSCEIVER 4BIT                 | 4   | E19,E20,E29,E30        |
| 4    | 4    |               | 1811660-02 | OSCILLATOR, CRYSTAL, 5.0688MHZ, 14PIN DIP   | 1   | Y1                     |
| 5    | 5    |               | 1912805-00 | LS08   AND GATE-QUAD 2IN,POSITIVE           | 2   | E4,E13                 |
| 6    | 6    |               | 1912803-00 | LS04   INVERTER GATE-HEX 1IN                | 1   | E11                    |
| 7    | 7    |               | 1912799-00 | LS00   NAND-GATE-QUAD 2IN,POSITIVE          | 1   | E3                     |
| 8    | 8    |               | 1911579-00 | 8641   TRANSCEIVER,BUS,QUAD,UNIBUS          | 1   | E2                     |
| 9    | 9    |               | 2112623-00 | DUAL BAUD RATE GEN/PROG DIVIDER,MOS   18P   | 1   | E9                     |
| 10   | 10   |               | 1912867-00 | LS298   MUX   1 OF   4,2IN W/STORAGE        | 1   | E8                     |
| 11   | 11   | (SEE NOTE 66) | 1913414-00 | LS14   INVERTER GATE-HEX SCHMITT TRIG       | 1   | E16                    |
| 12   | 12   |               | 1912801-00 | DEC   LS02   NOR GATE-QUAD 2IN              | 1   | E14                    |
| 13   | 13   |               | 1912813-00 | LS27   NOR GATE-TRIPLE 3IN                  | 1   | E7                     |
| 14   | 14   |               | 1912816-00 | LS32   OR GATE-QUAD 2IN,POSITIVE            | 1   | E12                    |
| 15   | 15   |               | 1912824-00 | LS74   FF-D DUAL,EDGE TRIGGER,POS           | 2   | E25,E21                |
| 16   | 16   |               | 1912845-00 | LS153   MUX   1 OF   4 (DUAL) & DATA SEL    | 1   | E17                    |
| 17   | 17   |               | 1911527-00 | 8097   BUFFER GATE-HEX 2INPUT TRI-STA       | 2   | E22,E31                |
| 18   | 18   |               | 1912647-00 | LS257   MUX   1 OF   2 (QUAD) TRI-STA       | 3   | E24,E27,E32            |
| 19   | 19   |               | 1912849-00 | LS161   COUNTER,SYNCHR,4BIT BINARY          | 1   | E15                    |
| 20   | 20   |               | 1910322-00 | DEC   1488L   DRIVER,LINE,QUAD,EIA RS-232C  | 1   | E18                    |
| 21   | 21   |               | 1910323-00 | DEC   1489L   RECEIVER,LINE,QUAD,EIA RS-232 | 1   | E28                    |
| 22   | 22   |               | 2111450-00 | UART 40K BAUD VARIATION OF 19-10459-00      | 1   | E23                    |
| 23   | 23   |               | 1914432-00 | 75454   DRIVER,PERIPH,DUAL,NOR              | 1   | E5                     |
| 24   | 24   |               | 1911998-02 | 4N26-20PFO COUPLED ISLTR   6 P              | 2   | E26,E33                |
| 25   | 25   |               | 1001765-00 | 5000.0 MMF 100V 20%   Z5U DISC#             | 1   | C29                    |
| 26   | 26   |               | 1000024-00 | 470.0 MMF 100V   5%200PPM DM15S   (10-00    | 3   | C23,C24,C28            |
| 27   | 27   |               | 1001610-01 | .01   MFD   100V OR 50V Z5U DISC/800PF MIN  | 18  | C3-C12,C15,C17-C22,C26 |
| 28   | 28   |               | 1012084-01 | 8   MFD   25V   G%   30D AL EL   (10-12     | 4   | C1,C2,C13,C14          |
| 29   | 29   |               | 1005306-00 | 6.8MFD   35V 10%   150D S.TA   (10-00       | 1   | C27                    |
| 30   | 30   |               | 1105275-00 | D 672   TR= 15NS PIV= 60V SP                | 4   | D1,D3-D5               |

| REVISION HISTORY |        |     | VARIATIONS FOR THIS ASSY. |  | FIRST USED ON:       |  | DIGITAL EQUIPMENT CORPORATION<br>MAYNARD, MASSACHUSETTS |  |                             |       |
|------------------|--------|-----|---------------------------|--|----------------------|--|---------------------------------------------------------|--|-----------------------------|-------|
| CHK              | ECD NO | REV |                           |  |                      |  |                                                         |  |                             |       |
| B.F              | 00002  | C   | 00                        |  | MADE BY: F SMART     |  | DATE: 26-MAY-78                                         |  | TITLE                       |       |
|                  |        |     |                           |  | CHECKED: F SMART     |  | DATE: 26-MAY-78                                         |  | PARTS LIST                  |       |
|                  |        |     |                           |  | DSN.ENG.: M MICHAUD  |  | DATE: 26-MAY-78                                         |  | ASYNCHRONOUS LINE INTERFACE |       |
|                  |        |     |                           |  | PROD.: KM            |  | DATE: 26-MAY-78                                         |  | SIZE                        | CODE  |
|                  |        |     |                           |  | RESP.ENG.: M MICHAUD |  | DATE: 26-MAY-78                                         |  | DOCUMENT NUMBER             | REV   |
|                  |        |     |                           |  |                      |  |                                                         |  | K                           | PL    |
|                  |        |     |                           |  |                      |  |                                                         |  | M8028-0-DBP                 | C     |
|                  |        |     |                           |  |                      |  |                                                         |  | ASSY.NO.: D-UA-M8028-0-0    | EDIT# |
|                  |        |     |                           |  |                      |  |                                                         |  |                             | 4     |

THIS DRAWING AND SPECIFICATIONS HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.

COPYRIGHT   1978. DIGITAL EQUIPMENT CORPORATION


| LINE | ITEM | DOCUMENT NO.     | PART NO.   | DESCRIPTION                              | QTY | REFERENCE DESIGNATORS     |
|------|------|------------------|------------|------------------------------------------|-----|---------------------------|
| 31   | 31   |                  | 1105610-00 | MCL1301 CL01MA FROM10-80V                | 1   | D6                        |
| 32   | 32   | (SEE NOTE 68)    | 1109502-01 | Z 6214 VZ= 12.0 2% 1W                    | 1   | D2                        |
| 33   | 33   |                  | 1300479-00 | 10 K 1/4W 5% CC (13-00                   | 9   | R1,R11-R15,R18,R19,R42    |
| 34   | 34   |                  | 1300365-00 | 1 K 1/4W 5% CC (13-00                    | 7   | R7,R8,R16,R35,R36,R38,R24 |
| 35   | 35   |                  | 1300295-00 | 330 1/4W 5% CC (13-00                    | 3   | R2,R4,R5                  |
| 36   | 36   |                  | 1300229-00 | 100 1/4W 5% CC (13-00                    | 1   | R21                       |
| 37   | 37   |                  | 1301424-00 | 680 1/4W 5% CC (13-00                    | 3   | R3,R6,R29                 |
| 38   | 38   |                  | 1303177-00 | 2.4 K 1/4W 5% CC (13-00                  | 2   | R9,R10                    |
| 39   | 39   |                  | 1300391-00 | 1.5 K 1/4W 5% CC (13-00                  | 1   | R17                       |
| 40   | 40   |                  | 1915249-00 | 74390 COUNTER,DECADE-DUAL,4BIT           | 1   | E6                        |
| 41   | 41   |                  | 1300316-00 | 470 1/4W 5% CC (13-00                    | 1   | R22                       |
| 42   | 42   |                  | 1312384-05 | 82 1W 5%                                 | 1   | R23                       |
| 43   | 43   |                  | 1300271-00 | 220 1/4W 5% CC (13-00                    | 1   | R25                       |
| 44   | 44   |                  | 1301972-00 | 270 1/4W 5% CC (13-00                    | 1   | R26                       |
| 45   | 45   |                  | 1301322-00 | 180 1/4W 5% CC (13-00                    | 2   | R27,R33                   |
| 46   | 46   |                  | 1300316-00 | 470 1/4W 5% CC (13-00                    | 1   | R28                       |
| 47   | 47   |                  | 1300219-00 | 68 1/4W 5% CC (13-00                     | 1   | R30                       |
| 48   | 48   |                  | 1300202-00 | 47 1/4W 5% CC (13-00                     | 4   | R31,R32,R39,R40           |
| 49   | 49   |                  | 1301327-00 | 68 K 1/4W 5% CC (13-00                   | 1   | R34                       |
| 50   | 50   |                  | 1300432-00 | 3 K 1/4W 5% CC (13-00                    | 1   | R37                       |
| 51   | 51   |                  | 1510706-00 | XA 55 PNP 500MW SI 60 50 P               | 3   | Q2-Q4                     |
| 52   | 52   |                  | 1515018-00 | 2N 2905A PNP 600MW SI 40 100             | 1   | Q1                        |
| 53   | 53   |                  | 1510705-00 | XA 05 NPN 500MW SI 60 50 P               | 2   | Q5,Q6                     |
| 54   | 54   |                  | 1602723-02 | 270 UH 10% 260MA #WEE270                 | 1   | L1                        |
| 55   | 55   |                  | 1209941-02 | HEADER 100 40POS RT ANGLE \$             | 1   | J1                        |
| 56   | 56   | (SEE NOTE 67)    | 9009149-01 | PIN, STAKING, P.C.BOARD .025 SQUARE      | 100 |                           |
| 57   | 57   |                  | 9008337-06 | HANDLE, FLIP CHIP, MAGENTA               | 1   |                           |
| 58   | 58   |                  | 1209941-04 | HEADER RT ANGLE,RIGHT LATCH FOR          | 1   |                           |
| 59   | 59   |                  | 1209941-03 | HEADER RT ANGLE LEFT LATCH FOR           | 1   |                           |
| 60   | 60   |                  | 1010279-00 | .47 MFD 25V 20% 2C023 CER.\$             | 1   | C16                       |
| 61   | 61   |                  | 9009781-00 | SPACER, MODULE, MAGENTA                  | 1   |                           |
| 62   | 62   |                  | 9105740-55 | WIRE(WRAP)30AWG UL1423 (91-00 A/R        |     |                           |
| 63   | 63   | D-MD-5012611-0-0 | 5012611-00 | M8028                                    | 1   |                           |
| 64   | 64   |                  | 9007201-00 | TRANSIPADS #10253                        | 1   |                           |
| 65   | 65   |                  | 9006732-00 | EYELET, ROLLED FLANGE, .121 OD X .219 LG | 4   |                           |


66 NOTE: IF 1913414 IS NOT AVAILABLE, USE 1911324(7414)

67 NOTE: IF 9009149-01 IS NOT AVAILABLE, USE 9009149-00.


68 NOTE: THIS PART IDENTIFIES THE CATHODE WITH A SILVER BAR


| TITLE                                                   | PARTS LIST                    | SIZE | CODE | DOCUMENT NUMBER | REV |
|---------------------------------------------------------|-------------------------------|------|------|-----------------|-----|
| DIGITAL EQUIPMENT CORPORATION<br>MAYNARD, MASSACHUSETTS | ASYNCHCHRONOUS LINE INTERFACE | K    | PL   | M8028-0-DBP     | C   |

















"THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DIGITAL EQUIPMENT CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION. COPYRIGHT © 1974 DIGITAL EQUIPMENT CORPORATION"



# DIGITAL EQUIPMENT CORPORATION

## MAYNARD, MASSACHUSETTS

### PARTS LIST

|         |               |         |           |              |
|---------|---------------|---------|-----------|--------------|
| MADE BY | M. MICHAUD    | CHECKED | D. HEALY  | SECTION      |
| DATE    | 11 AUG 77     | DATE    | 11 AUG 77 | 1            |
| ENG     | M. D. Michaud | PROD    |           | ISSUED SECT. |
| DATE    | 18 Aug 77     | DATE    | 8-19-77   | 1            |

### QUANTITY VARIATION

[illegible]DEC FORM  
DRA 110

This drawing and specifications, herein, are the property of Digital Equipment Corporation and shall not be reproduced or copied or used in whole or in part as the basis for the manufacture or sale of items without written permission. COPYRIGHT © 1973

DIGITAL EQUIPMENT CORPORATION

| LEGEND   |           |           |
|----------|-----------|-----------|
| NUMBER   | VARIATION |           |
|          | LENGTH    | ITEM #1   |
| BCØ5M-2C | 27 IN.    | 7008360   |
| BCØ5M-04 | 48 IN.    | 7008360-1 |

NOTES:  
1. FOR ASSEMBLY SEE D-IA-7008360-0-0.

SEE NOTE #1

| REVISIONS        |             | REV. |
|------------------|-------------|------|
| CHK              | CHANGE NO.  |      |
| JL               | BCØ5M-00001 | A    |
| M.E. LEWANDOWSKI |             |      |
| 1-19-76          |             |      |
| M.E. LEWANDOWSKI |             |      |
| 1-28-76          |             |      |

|                                                           |         |                   |             |                                                                |      |
|-----------------------------------------------------------|---------|-------------------|-------------|----------------------------------------------------------------|------|
| FIRST USED ON OPTION/MODEL                                |         | QTY.              | CABLE ASSY. | SEE LEGEND                                                     | 1    |
| UNLESS OTHERWISE SPECIFIED<br>DIMENSION IN INCHES         |         | DESCRIPTION       |             |                                                                |      |
| TOLERANCES                                                |         | PARTS LIST        |             |                                                                |      |
| DECIMALS                                                  | ANGLES  | DRN.              | DATE        | <b>digital</b> EQUIPMENT CORPORATION<br>MAYNARD, MASSACHUSETTS |      |
| .xxx = .005                                               | ±0° 30' | CHK'D             | DATE        |                                                                |      |
| .xx = .02                                                 |         | ENG               | DATE        |                                                                |      |
| .x = .1                                                   |         | PROJ. ENG.        | DATE        |                                                                |      |
| REMOVE BURRS AND BREAK SHARP<br>CORNERS SURFACE QUALITY ✓ |         | PROD.             | DATE        | TITLE<br>BCØ5M<br>CABLE ASSEMBLY<br>(KL8-E, KL8-JA)            |      |
| MATERIAL<br>SEE PARTS LIST                                |         | NEXT HIGHER ASSY. |             |                                                                |      |
| FINISH                                                    |         | SCALE             |             | SIZE                                                           | CODE |
|                                                           |         | SHEET             |             | B                                                              | UA   |
|                                                           |         | OF                |             | NUMBER                                                         |      |
|                                                           |         |                   |             | BCØ5M-Ø-Ø                                                      |      |
|                                                           |         |                   |             | REV.                                                           |      |
|                                                           |         |                   |             | A                                                              |      |
|                                                           |         |                   |             | DIST.                                                          |      |
|                                                           |         |                   |             |                                                                |      |



